



*SpeedMixer*TM

German Engineering
by Hauschild



DAC 3000 / 5000 / 10000 HP



Please scan
for more
information
about our
products.






SpeedMixer™

GermanEngineering
by Hauschild

Technical Data



| | DAC 3000 HP | DAC 5000 HP | DAC 10000 HP |
|--------------------------|------------------------|------------------------|------------------------|
| Mixing Capacity Min/Max: | 1500g ÷ 3000g | 2500g ÷ 5000g | 3500 – 10000 g |
| Speed Min/Max: | 50 rpm ÷ 1000 rpm | 50 rpm ÷ 800 rpm | 50 rpm ÷ 800 rpm |
| Mixing Time Min/Max: | 5s ÷ 600s | 5s ÷ 600s | 5s ÷ 600s |
| Voltage - Frequency: | 380 - 500 V – 50/60 Hz | 380 - 500 V – 50/60 Hz | 380 - 500 V – 50/60 Hz |
| Input Power: | 5,5 KW | 5,5 KW | 7,0 KW |
| Height – Open Lid: | 1700 mm | 1700 mm | 1800 mm |
| Width: | 1710 mm | 1710 mm | 1710 mm |
| Depth: | 1200 mm | 1200 mm | 1200 mm |
| Weight: | 1200 kg | 1250 kg | 1700 kg |



Your Notes:

Subject to modifications – Last update 28/08/2018



Hauschild & Co. KG
 Waterkamp 1 · 59075 Hamm / Germany
 Phone +49 (0)2381 48205-0
 Telefax +49 (0)2381 48205-17
 E-Mail info@speedmixer.de
 www.speedmixer.de